

16-port Fast Ethernet Switch

ND-921-16TX



FEATURES

- Provide 16 10/100/1000M adaptive RJ45 ports
- All ports can achieve wire-speed forwarding;
- LED dynamic indicators for easy status indication and troubleshooting
- Low power fanless design, eliminating noise interference and improving product stability
- Support port automatic flip, more convenient to use
- Support MAC address self-learning



Newbridge® The ND-921-16TX 16-port 10/100/1000M unmanaged switch allows you to quickly, reliably and efficiently build wired networks in your home or office. The switch is designed to enhance the performance of small workgroups while providing network flexibility. The device is easy to use, users only need to connect the device to any port via a network cable. The ND-921-16TX can be connected to multiple computers for file sharing. Share your internet connection by connecting it to your router.

ND-921-16TX does not use wind Fan, can work quietly, so that you can watch streaming media from the network and browse the web quietly.

The ND-921-16TX is a plug and play device. Easily connect multiple computers with no configuration required for file, music and video sharing on a home or small office network. When the port's buffer is full, the 802.3x flow control feature minimizes packet loss, providing a more reliable data transfer connection for connected devices.

ND-921-16TX can adapt to 10/10/1000Mbps ports. Each port has LED indicators to indicate link connectivity and activity. These ports can detect network speed and auto-negotiate between 10BASE-T and 1000BASE-TX, as well as full-duplex and half-duplex, to provide the best possible network speed for every device connected to the network. The ND-921-16TX also supports automatic MDI/MDIX recognition, allowing you to use regular pass-through twisted pair cable to connect each port to a server, hub, router or other switch

Specifications

Product Name	16 Port 10/100/1000M Fast Ethernet switch
Product Model	ND-921-16TX
Interface	16x 10/100/1000Base-T ports
Network Protocols	IEEE802.3 10BASE-T; IEEE802.3i 10Base-T; IEEE802.3u 100Base-TX; IEEE802.3ab 1000Base-T;



Shenzhen Newbridge Communication Equipment CO.,LTD.

16-port Fast Ethernet Switch

ND-921-16TX



	IEEE802.3z 1000Base-X; IEEE802.3x
Network Media	10BASE-T: Cat3,4,5 UTP 100BASE-TX: Cat5 or later UTP 1000BASE-TX: Cat5 or later UTP
Performance Specification	Bandwidth: 32Gbps Packet Buffer Memory:1Mbits 10 Mbps Packet Forwarding Rate: 14880 pps/port 100Mbps Packet Forwarding Rate:148800 pps/port MAC Address Table: 2K Switching Delay: <10us
Forwarding Mode	Store-and-Forward
LED Indicators	Power: PWR; Link: Link/Act
Power Supply	Input Power: 100-240V ~ 50/60Hz AC Working Consumption : <1W
Working Environment	Working temperature: 0~+40℃ ; Storage temperature: -40~+70℃ Relative Humidity: 5%~90 % (no condensation)
Packing List	1×Industrial16-port Fast Ethernet Switch 1×User Manual/Certificate of quality/Warranty card 1×Power Adapter
MTBF	300,000 hours

Order Information

Part No	Description of product	Unit
ND-921-16TX	16*10/100/1000M Base-Tx Fast Ethernet Switch	pc